



Tel: (613) 748-0432
Fax: (613) 748-0355

A Division of the S&S Bolton Group
www.ssbolton.com

SITE INSTRUCTIONS

Ref: SS4258 Rev.02

Customer:

Hikmat Hisham Albatarni & Tara Mazen Matar

Builder: VALECRAFT HOMES LTD.
Project: Deerfield Village Condos
Lot: DV2 S15
Closing Date: 02/10/2022

Salesperson: Jason Thompson
Date: 01/25/2021

Location	Qty	Product / Installation Details	Plan Code
Living Room	1.00	15 Amp Standard Plug Add 15 AMP plug approx 60 inches from floor beside conduit	A
Master Bedroom	1.00	15 Amp Standard Plug Add 15 AMP plug approx 60 inches from floor beside conduit	B
Kitchen	1.00	Standard Light Outlet (Keyless) Relocate standard fixture and leave as keyless fixture and add 2nd keyless fixture for future pendant lighting	C
Kitchen	1.00	4" LED slim Pot Light White (AFR4C-0930-WH) Add 3 LED Halo potlights (AFR4-0930-WH) on added switch	D
Kitchen	1.00	Single Pole Switch Switch for kitchen potlight	D
Living Room	1.00	6 * 4" LED slim Pot Light White (AFR4C-0930-WH) Add 6 LED Halo potlights (AFR4-0930-WH) on added 3/way switch	E
Living Room	2.00	Single Pole Switch Switch for living room potlights	E
Ensuite Bath	1.00	4" LED slim Pot Light White (AFR4C-0930-WH) Add 1 LED Halo potlight (AFR4-0930-WH) on added switch	F
Ensuite Bath	1.00	Single Pole Switch Switch for added potlight	F
Main Bath	1.00	4" LED slim Pot Light White (AFR4C-0930-WH) Add 1 LED Halo potlight (AFR4-0930-WH) on added switch	G
Main Bath	1.00	Single Pole Switch Switch for added potlight	G
Kitchen	1.00	20 Amp USB Charger Receptacle 20 Amp USB Charger Receptacle (standard)	H
Living Room	1.00	15 Amp Standard Plug 15 Amp Standard Plug and create 4/gang	I

Phone: (613) 748-0432 | Fax: (613) 748-0355 | Email: info@sandselectric.ca | Website: www.sandselectric.ca

5411 Canotek Road, Ottawa, Ontario K1J 9M3

Printed By: Jason Thompson - Page: 1



Tel: (613) 748-0432
Fax: (613) 748-0355

Location	Qty	Product / Installation Details	Plan Code
Dining	1.00	2 * 4" LED slim Pot Light White (AFR4C-0930-WH) Add 2 LED Halo potlights (AFR4-0930-WH) on added dimmer switch	J
Dining	1.00	Add Dimmer Add Dimmer	J
Dining	1.00	15 Amp Standard Plug Relocate standard plug and add (1) 15 Amp Plug	K
Various Locations	2.00	Upgrade Switch to Dimmer Upgrade Switch to Dimmer in kitchen and living room	L
Kitchen	1.00	LED Stick (Varies Per Kitchen Layout - To Be Quoted) Add under cabinet LED Stick lighting on added switch	M
Kitchen	1.00	Single Pole Switch Switch for under cabinet lighting	M

Notes:

"Purchaser has acknowledged that they have discussed any kitchen layout modifications with their electrical representative. If modifications are made after signing off on electrical, this will incur additional charges."